### UNI-T

# UT333S

## **Digital Temperature Humidity** Meter User Manual

### Introduction

UT333S is a stable, safe and reliable mini digital temperature humidity meter, which is widely used in grain storage and transportation, file management, material management, forestry and animal husbandry, health care, teaching experiment, public sector and home.

#### Features:

- Precise temperature and humidity sensor
- Split type design with extendable spring cable for convenient measurement

Before using this device, please read all safety information, warnings and notes carefully.

### Package list

Open the package and take out the meter, please check carefully if the following items are missing or damaged.

- 1. A device
- 2. A temperature and humidity probe
- 3. A set of blister
- 4. A manual

### Safety information

- 1. Before using the meter, please check it and the accessories for any damage or anomaly. Do not use the meter if its case is apparently damaged or LCD screen shows nothing or it is suspected not working properly.
- 2. Please follow the operation instructions during measurement.
- 3. Do not dismount the device and change the internal wiring.
- 4. When symbol appears on the screen, please replace the batteries soon. Take out the batteries if the meter is not used for long time.
- 5. Do not store or use this meter in high temperature, high humidity, flammable, explosive and strong electromagnetic environments.
- 6. Please use soft cloth and neutral detergent to clean the case. Do not use abradant or solvent or it will cause corrosion


### **Structure**

- 1. Sensor
- 2. Test lead handle
- 3. LCD screen
- 4. Function key
- 5. Probe holder

# 00

### **Symbol**

- 1. Maximum value
- 2. Minimum value
- 3. Data hold
- 4. Low power
- 5. Relative humidity
- 6. Fahrenheit degree
- 7. Celsius degree
- 8. Temperature value
- 9. Auto power off
- 10. Humidity value



### **Buttons& Setting**

1. 也: ON/OFF

Under OFF status: long press this button to turn on the device. Under ON status: long press this button to enable or disable auto power off function, short press to turn off the device.

- 2. °C/°F: short press this button to switch temperature units
- 3. MODE: Short press this button to switch through maximum/minimum/
- 4. HOLD/BL: short press this button to enable/disable data hold function, long press this button to turn on/off the backlight.

### **Technical specifications**


Function	Range	Resolution	Accuracy	Note
Humidity	0~100.0%RH		20~80%RH: ±5%RH Other: ±8%RH	Ambient temperature
Temperature	-10~60°C	0. 1°C	±1.0°C	Ambient humidity
	14~140°F	0. 2°F	±2.0°F	

Function	Description		
Unit switch	Selectable temperature unit		
Extreme value	Maximum/minimum value		
Data hold	HOLD symbol appears		
Overload alarm	When the humidity exceeds 100.0%RH, 100.0%RH is shown on the screen; when the temperature exceeds 60°C, OL symbol is shown; when the temperature lower than 20°C, -OL is shown.		
Backlight	Backlight function		
Auto power off	The device will turn off automatically without operation for 5 minutes		
Sampling rage	Once/second		
Drop test	1m		
Battery	1.5V AAA*3		
Operating environment	Indoor 0°C~40°C (≤90%RH)		
Storage environment	Indoor -20°C~60°C (≤75%RH)		
Altitude	2000m		
Pollution grade	2		

### **Maintenance**

⚠ Warning: Please do not dismount the case or it will damage the device or influence the accuracy.

- a. Regularly use dry cloth to clean the case. Do not use detergent containing solvents.
- b. If the following anomaly occurs, please contact our customer service or sales agents for repair.
- c. Install or replace the batteries (1.5V AAA\*3) according to the figure below:



# LINI-T

### UNI-TREND TECHNOLOGY (CHINA) CO., LTD.

No6, Gong Ye Bei 1st Road, Songshan Lake National High-Tech Industrial Development Zone, Dongguan City, Guangdong Province, China Tel: (86-769) 8572 3888 http://www.uni-trend.com

